Connection and Function List of AD-8922A Remote Controller

Series/Model	RS232C output interface (Option name if required)	Required Cable	Connection cable used when installing the AD8922A-01	ON:OFF	CAL	SAMPLE	PRINT	MODE	RE-ZERO	Command set (AD-8922A function settings)	Remarks
BM	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	
BA-T	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	-	Yes	-	Yes	CSet 1	AX-KO2741-180: Balance and AD8922A operable with one AC adapter. *1
BA	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AX-KO2741-180: Balance and AD8922A operable with one AC adapter. *1
BH-T	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	-	Yes	-	Yes	CSet 1	
BH	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	
GH	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	
GR	Standard (D-Sub9P)	AX-KO1710-200	AX-KO577A-200	Yes	Yes	Yes	Yes	Yes	Yes	CSet 2	
HR	Standard (D-Sub9P)	AX-KO1710-200	AX-KO577A-200	Yes	-	Yes	Yes	Yes	Yes	CSet 3	
HR-i	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	-	Yes	Yes	Yes	Yes	CSet 3	
HR-A	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	-	Yes	Yes	Yes	Yes	CSet 3	AX-KO2741-180: Balance and AD8922A operable with one AC adapter. *1
HR-AZ	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AX-KO2741-180: Balance and AD8922A operable with one AC adapter. *1
GF-A	Standard (D-Sub9P) or GXA-03	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	-	Yes	Yes	Yes	Yes	CSet 3	AX-KO2741-180: Balance and AD8922A operable with one AC adapter. *1
GX-A	Standard (D-Sub9P) or GXA-03	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AX-KO2741-180: Balance and AD8922A operable with one AC adapter. *1
GF-AWP	Standard (D-Sub9P) or GXA-03	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	-	Yes	Yes	Yes	Yes	CSet 3	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8922A operable with one AC adapter. *1
GX-AWP	Standard (D-Sub9P) or GXA-03	AX-KO2737-500EX (Balance-side Dust/Waterproof)	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8922A operable with one AC adapter. *1
GF-M	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	-	Yes	Yes	Yes	Yes	CSet 3	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8922A operable with one AC adapter. *1
GX-M	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8922A operable with one AC adapter. *1
GF-L	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	-	Yes	Yes	Yes	Yes	CSet 3	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8922A operable with one AC adapter. *1
GX-L	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8922A operable with one AC adapter. *1
GF	Standard (D-Sub25P) or GX-04 (D-Sub25P)	AX-KO1710-200	AX-KO577A-200	Yes	-	Yes	Yes	Yes	Yes	CSet 3	
GX	Standard (D-Sub25P) or GX-04 (D-Sub25P)	AX-KO1710-200	AX-KO577A-200	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	
FX	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	-	Yes	Yes	Yes	Yes	CSet 3	AX-KO2741-180: Balance and AD8922A operable with one AC adapter. *1
FZ	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AX-KO2741-180: Balance and AD8922A operable with one AC adapter. *1
FX-WP	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	-	Yes	Yes	Yes	Yes	CSet 3	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8922A operable with one AC adapter. *1
FZ-WP	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8922A operable with one AC adapter. *1
FX-i	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	-	Yes	Yes	Yes	Yes	CSet 3	AX-KO2741-180: Balance and AD8922A operable with one AC adapter. *1
FZ-i	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AX-KO2741-180: Balance and AD8922A operable with one AC adapter. *1
FX-iWP	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	-	Yes	Yes	Yes	Yes	CSet 3	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8922A operable with one AC adapter. *1
FZ-iWP	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8922A operable with one AC adapter. *1
GF-K	Standard (D-Sub25P) or GX-04K (D-Sub25P)(non-waterproof)	GX-07K (Balance-side Dust/Waterproof) AX-KO1710-200	AX-KO577A-200	Yes	-	Yes	Yes	Yes	Yes	CSet 3	
GX-K	Standard (D-Sub25P) or GX-04K (D-Sub25P)(non-waterproof)	GX-07K (Balance-side Dust/Waterproof) AX-KO1710-200	AX-KO577A-200	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	
GP	Standard (D-Sub25P) or GP-04 (D-Sub25P)	AX-KO1710-200	AX-KO577A-200	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	
MC-A	Standard (D-Sub9P) or GXA-03	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AX-KO2741-180: Balance and AD8922A operable with one AC adapter. *1
MC-M	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8922A operable with one AC adapter. *1
MC1000/6100	Standard (D-Sub25P) or GX-04 (D-Sub25P)	AX-KO1710-200	AX-KO577A-200	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	
MC10K/30K	Standard (D-Sub25P) or GX-04K (D-Sub25P)(non-waterproof)	GX-07K (Balance-side Dust/Waterproof) AX-KO1710-200	AX-KO577A-200	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	
MC100KS	Standard (D-Sub25P) or GP-04 (D-Sub25P)	AX-KO1710-200	AX-KO577A-200	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	
AD4212A	Standard (D-Sub25P) or AD4212A-04 (D-Sub25P)	AX-KO1710-200	AX-KO577A-200	Yes	-	Yes	Yes	Yes	Yes	CSet 3	
AD4212B	Standard (D-Sub25P)	AX-KO1710-200	AX-KO577A-200	Yes	-	Yes	Yes	Yes	Yes	CSet 3	
AD4212C	Standard (12-pin waterproof circular)	Cable included with AD4212C	AX-KO3705-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AD4212C and AD8922A operable with one AC adapter. *2
AD4212D	Standard (12-pin waterproof circular)	Cable included with AD4212D	AX-KO3705-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	CSet 1	AD4212D and AD8922A operable with one AC adapter. *2
AD4212F	Standard (12-pin waterproof circular)	AX-KO3590-200／500／1000	AX-KO3705-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	Cset 1	AD4212F and AD8922A operable with one AC adapter. *2
EJ	EJ-03 (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	-	-	-	Yes	Yes	Yes	CSet 4	
EK	Standard (D-Sub9P)	AX-KO2466-200	AX-KO1786-200/500/1000	-	-	-	Yes	Yes	Yes	CSet 4	AX-KO2741 cannot be used
EK-i /EW-i	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	-	-	-	Yes	Yes	Yes	CSet 4	
EK-L	EJ-03 (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	-	-	-	Yes	Yes	Yes	CSet 4	AX-KO2741-180: EK-L and AD8922A operable with one AC adapter. *1
EK-AEP	AD1611 (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	-	-	-	-	-	-	-	Weight output only (no command mode) Use optional optical cable AX-KS5456-xxx for EK-AEP–AD1611 connection
FG	FG-23 (Din8P)	AX-KO1786-200	AX-KO507-W200	-	-	-	Yes	-	-	CSet 0	
FS	FS-03 (Din7P)	AX-KO1786-200	AX-KO507-W200	-	-	-	Yes	-	-	CSet 0	
FS-i	FS-03i (Terminal block)	AX-KO3285-320	AX-KO507-S200 or AX-KO5862-S200	-	-	-	Yes	-	-	CSet 0	
HV-G / HW-G	Standard (Din7P)	AX-KO1786-200	AX-KO507-W200	-	-	-	Yes	-	-	CSet 0	
HV-C / HW-C	HVW-03C (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	-	-	-	Yes	-	-	CSet 0	
HV-CWP / HW-CWP	HVW-03CWP (Terminal block)	AX-KO3285-320	AX-KO507-S200 or AX-KO5862-S200	-	-	-	Yes	-	-	CSet 0	
SC/SE	SCE-03 (Terminal block)	AX-KO3285-320	AX-KO507-S200 or AX-KO5862-S200	-	-	-	Yes	-	Yes	CSet 4	
SW	SW-03 (Terminal block)	AX-KO3285-320	AX-KO507-S200 or AX-KO5862-S200	-	-	-	Yes	-	-	CSet 0	RE-ZERO = ZERO key
FC-i/Si	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	AX-KO1786-200/500/1000	-	-	-	Yes	-	-	CSet 0	Output: count or weight only
HC-i	HC-03i (Din8P)	AX-KO1786-200	AX-KO507-W200	-	-	-	Yes	-	-	CSet 0	Output: count or weight only
HD	HD-03i (D-sub25P)	AX-KO1710-200	AX-KO577A-200	-	-	-	Yes	-	-	CSet 0	Output: count or weight only
GC	Standard (D-Sub9P)	AX-KO2466-200	AX-KO1786-200/500/1000	-	-	-	Yes	Yes	-	CSet 0	Output: count or weight only, comparison result optional AX-KO2741 cannot be used
HT/HT-CL	Connection unavailable										
HT-120	Connection unavailable										
FG-CWP	Connection unavailable										
HL-i	Connection unavailable										
SJ-HS	Connection unavailable										
SK-WP/SK	Connection unavailable										
HV-CEP / HW-CEP	Connection unavailable										
FG-CWP	Connection unavailable										

*1: When the AD8922A-01 is installed, operation with a single AC adapter is not possible. An AC adapter is required on both the balance side and the AD8922A side.
*2: Even when the AD8922A-01 is installed, operation with a single AC adapter is possible when using the AX-KO3705-200/500/1000.