Connection and Function List of AD8923CC/BCD

Series/Model	RS232C output interface (Option name if required)	Required Cable	ON:OFF	CAL	SAMPLE	PRINT	MODE	RE-ZERO	Remarks
BM	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	Yes	Yes	Yes	Yes	Yes	Yes	
BH	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	Yes	Yes	Yes	Yes	Yes	Yes	
GH	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	Yes	Yes	Yes	Yes	Yes	Yes	
GR	Standard (D-Sub25P)	AX-KO1710-200	Yes	Yes	Yes	Yes	Yes	Yes	
HR	Standard (D-Sub25P)	AX-KO1710-200	Yes	–	Yes	Yes	Yes	Yes	
HR-i	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	Yes	–	Yes	Yes	Yes	Yes	
HR-A	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	Yes	–	Yes	Yes	Yes	Yes	AX-KO2741-180: Balance and AD8923 operable with one AC adapter.
HR-AZ	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	Yes	Yes	Yes	Yes	Yes	Yes	AX-KO2741-180: Balance and AD8923 operable with one AC adapter.
GF-A	Standard (D-Sub9P) or GXA-03	AX-KO2741-180 or AX-KO2466-200	Yes	–	Yes	Yes	Yes	Yes	AX-KO2741-180: Balance and AD8923 operable with one AC adapter.
GX-A	Standard (D-Sub9P) or GXA-03	AX-KO2741-180 or AX-KO2466-200	Yes	Yes	Yes	Yes	Yes	Yes	AX-KO2741-180: Balance and AD8923 operable with one AC adapter.
GF-AWP	Standard (D-Sub9P)or GXA-03	AX-KO2737-500EX (Balance-side Dust/Waterproof)	Yes	–	Yes	Yes	Yes	Yes	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8923 operable with one AC adapter.
GX-AWP	Standard (D-Sub9P)or GXA-03	AX-KO2737-500EX (Balance-side Dust/Waterproof)	Yes	Yes	Yes	Yes	Yes	Yes	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8923 operable with one AC adapter.
GF-M	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	Yes	–	Yes	Yes	Yes	Yes	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8923 operable with one AC adapter.
GX-M	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	Yes	Yes	Yes	Yes	Yes	Yes	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8923 operable with one AC adapter.
GF-L	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	Yes	–	Yes	Yes	Yes	Yes	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8923 operable with one AC adapter.
GX-L	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	Yes	Yes	Yes	Yes	Yes	Yes	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8923 operable with one AC adapter.
GF	Standard (D-Sub25P) or GX-04 (D-Sub25P)	AX-KO1710-200	Yes	–	Yes	Yes	Yes	Yes	
GX	Standard (D-Sub25P) or GX-04 (D-Sub25P)	AX-KO1710-200	Yes	Yes	Yes	Yes	Yes	Yes	
FZ/FZ-i	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	Yes	Yes	Yes	Yes	Yes	Yes	AX-KO2741-180: Balance and AD8923 operable with one AC adapter.
FX/FX-i	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	Yes	–	Yes	Yes	Yes	Yes	AX-KO2741-180: Balance and AD8923 operable with one AC adapter.
FX-WP/FX-iWP	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	Yes	–	Yes	Yes	Yes	Yes	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8923 operable with one AC adapter.
FZ-WP/FZ-iWP	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	Yes	Yes	Yes	Yes	Yes	Yes	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8923 operable with one AC adapter.
GF-K	Standard (D-Sub25P) or GX-04K (D-Sub25P)	GX-07K (Balance-side Dust/Waterproof) AX-KO1710-200	Yes	–	Yes	Yes	Yes	Yes	
GX-K	Standard (D-Sub25P) or GX-04K (D-Sub25P)	GX-07K (Balance-side Dust/Waterproof) AX-KO1710-200	Yes	Yes	Yes	Yes	Yes	Yes	
GP	Standard (D-Sub25P) or GP-04 (D-Sub25P)	AX-KO1710-200	Yes	Yes	Yes	Yes	Yes	Yes	
MC-A	Standard (D-Sub9P) or GXA-03	AX-KO2741-180 or AX-KO2466-200	Yes	Yes	Yes	Yes	Yes	Yes	AX-KO2741-180: Balance and AD8923 operable with one AC adapter.
MC-M	Standard (D-Sub9P)	AX-KO2737-500EX (Balance-side Dust/Waterproof) AX-KO2741-180 or AX-KO2466-200	Yes	Yes	Yes	Yes	Yes	Yes	AX-KO2741-180 or AX-KO2737-500EX: Balance and AD8923 operable with one AC adapter.
MC-1000/6100	Standard (D-Sub25P) or GX-04 (D-Sub25P)	AX-KO1710-200	Yes	Yes	Yes	Yes	Yes	Yes	
MC-10K/30K	Standard (D-Sub25P) or GX-04K (D-Sub25P)	GX-07K (Balance-side Dust/Waterproof) AX-KO1710-200	Yes	Yes	Yes	Yes	Yes	Yes	
MC-100KS	Standard (D-Sub25P) or GP-04 (D-Sub25P)	AX-KO1710-200	Yes	Yes	Yes	Yes	Yes	Yes	
AD4212A	Standard (D-Sub25P) or AD4212A-04 (D-Sub25P)	AX-KO1710-200	Yes	–	Yes	Yes	Yes	Yes	
AD4212B	Standard (D-Sub25P)	AX-KO1710-200	Yes	–	Yes	Yes	Yes	Yes	
AD4212C	Standard (D-Sub9P)	Cable included with AD4212C	Yes	Yes	Yes	Yes	Yes	Yes	AD4212C and AD8923 operable with one AC adapter.
AD4212D	Standard (D-Sub9P)	Cable included with AD4212D	Yes	Yes	Yes	Yes	Yes	Yes	AD4212D and AD8923 operable with one AC adapter.
AD4212F	Standard (D-Sub9P)	AX-KO7796-200/500/1000	Yes	Yes	Yes	Yes	Yes	Yes	AD4212F and AD8923 operable with one AC adapter.
EJ	EJ-03 (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	–	–	–	Yes	Yes	Yes	
EK	Standard (D-Sub9P)	AX-KO2466-200	–	–	–	Yes	Yes	Yes	
EK-i /EW-i	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	–	–	–	Yes	Yes	Yes	
EK-L	Standard (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	–	–	–	Yes	Yes	Yes	
FG	FG-23 (Din8P)	AX-KO1786-200	–	–	–	Yes	–	–	
FG-CWP	Connection unavailable		–	–	–	–	–	–	Not connectable because no RS-232C interface is provided
FS-i	FS-03i (Terminal block)	AX-KO3285-320	–	–	–	Yes	–	–	
HV-G / HW-G	Standard (Din8P)	AX-KO1786-200	–	–	–	Yes	–	–	
HV-C / HW-C	HVW-03C (D-Sub9P)	AX-KO2741-180 or AX-KO2466-200	–	–	–	Yes	–	–	
HV-CWP / HW-CWP	HVW-03CWP (Terminal block)	AX-KO3285-320	–	–	–	Yes	–	–	
SC/SE	SCE-03 (Terminal block)	AX-KO3285-320	–	–	–	Yes	–	Yes	
SW	SW-03 (Terminal block)	AX-KO3285-320	–	–	–	Yes	–	–	
FC-i/Si	Connection unavailable		–	–	–	–	–	–	Not connectable because QT header for count data is not supported
HC-i	Connection unavailable		–	–	–	–	–	–	Not connectable because QT header for count data is not supported
HD	Connection unavailable		–	–	–	–	–	–	Not connectable because QT header for count data is not supported
GC	Connection unavailable		–	–	–	–	–	–	Not connectable because QT header for count data is not supported